

NAME

stty – set teletype options

SYNOPSIS

stty option ...

DESCRIPTION

Stty will set certain I/O options on the current output teletype. The option strings are selected from the following set:

even	allow even parity
-even	disallow even parity
odd	allow odd parity
-odd	disallow odd parity
raw	raw mode input (no erase, kill, interrupt, quit, EOT; parity bit passed back)
-raw	negate raw mode
-nl	allow carriage return for new-line, and output CR-LF for carriage return or new-line
nl	accept only new-line to end lines
echo	echo back every character typed
-echo	do not echo characters
lcase	map upper case to lower case
-lcase	do not map case
-tabs	replace tabs by spaces in output
tabs	preserve tabs
delay	calculate cr, tab, and form-feed delays
-delay	no cr/tab/ff delays
tdelay	calculate tab delays
-tdelay	no tab delays

SEE ALSO

stty (II)

BUGS

There should be ‘package’ options such as **execuport**, **33**, or **terminet**.